

65 WATTS DVD/USB P.A. AMPLIFIER A.C & 12V DC (BATTERY) OPERATION

FEATURES :

DVD, 3 MIC & 1AUX,USB INPUT

DVD audio/video can be played, Up to 3 mics can be connected.The AUX input is for connecting cassette player/cd player/mixer.USB i/p is to connect USB drives.

FM TUNER :

Built in FM tuner that can be tuned to available stations.

REMOTE CONTROL :

Remote control has all the functions like vol. control input selection etc.

tone CONTROL (BASS/TREBLE) :

Desired frequencies can be obtained for speech and music

OUTPUT INDICATOR :

Five LED bargraph to monitor amplifier output.

VOLUME CONTROL (MASTER) :

Controls the overall volume level of inputs.

PROTECTION :

A protection FUSE (8 A DC) is provided in case battery is wrongly connected. 3 Amp Ac fuse for short circuit protection



SPECIFICATIONS

| | | | |
|--|--|-----------------------|--|
| MODEL | SMDA-65 USB | PRE OUT | 200mV / 1Kohm |
| POWER REQUIREMENTS | AC: 220-240V 50/60 HZ DC: 12 V Car Battery | SIGNAL TO NOISE RATIO | -65 dB |
| POWER CONSUMPTION ON FULL LOAD | AC-180 VA DC- 4Amp | OUTPUT TAPS | COM-4 ohm, 8 ohm, 16 ohm 0-70V-100V |
| POWER OUTPUT R.M.S. | Max. - 130 Watts At 10% THD - 90 Watts At 5 % THD - 80 Watts At 2% THD - 70 Watts | TONE CONTROL | BASS ± 10 dB at 100 Hz TREBLE ± 10 dB at 10 KHz |
| OUTPUT REGULATION | ≤2 dB at No Load to Full Load | PROTECTION | 3 Amp-AC FUSE 8 Amp-DC FUSE |
| MIC 1-5 INPUT SENSIVITY AUX 1-2 | 0.8mV / 3.3 Kohm 80 mV / 100 Kohm | NET WEIGHT | 9 Kgs |
| FREQUENCY RESPONSE at -10 dB from rated output | 70 Hz To 15KHz | OUTPUT INDICATOR | 5 LED BARGRAPH |